




Learn more about  
this product





## Your Gateway to Efficient Connectivity

The Kvaser Leaf Light R v2 is the rugged version of Kvaser's popular Leaf Light v2 interface. This is a single channel CAN bus interface with a lightweight yet highly durable, IP65-rated housing that assures reliable protection against water and dust ingress. Vibration, shock and drop proof, this interface belongs to Kvaser's Rugged range and operates over a temperature range of -40 to +70 °C.

With a standard USB2.0 connection and a high-speed CAN channel in a 9-pin D-SUB CAN connector, the Kvaser Leaf Light R v2 handles transmission and reception of standard and extended CAN messages, with a time stamp precision of 100 microseconds. Features include error frame detection and LED indicators for power and CAN channel status.

 **Warranty**  
2-Year warranty. See our general conditions and policies for details.

 **Support**  
Free support for all products by contacting [support@kvaser.com](mailto:support@kvaser.com)

 **EAN**  
73-30130-00921-9

## Major Features

- IP65 rated lightweight aluminum housing, sealed with polyurethane coating.
- Capable of sending up to 8000 messages per second, time-stamped with 100 microsecond accuracy.
- Quick and easy plug-and-play installation.
- Supports High Speed CAN (ISO 11898-2) up to 1 Mbit/s.
- Supports both 11-bit (CAN 2.0A) and 29bit (CAN 2.0B active) identifiers.
- Power is taken from the USB bus.
- Detection of error frames.
- LED lights alert user to device status.
- 100% compatible with applications written for other Kvaser CAN hardware with Kvaser CANlib.
- Operating temperature range from -40 to 70 °C.
- Compatible with J1939, CANopen, NMEA 2000® and DeviceNet. Higher layer protocol translation handled by the user's application. For software support please see our Technical Associates products and our Software Download page ([www.kvaser.com](http://www.kvaser.com)).

## Support

Documentation, Kvaser CANlib SDK and drivers can be downloaded for free at [www.kvaser.com/downloads](http://www.kvaser.com/downloads).

Kvaser CANlib SDK is a free resource that includes everything you need to develop software for the Kvaser CAN interfaces. Includes full documentation and many program samples, written in C, C++, C#, Delphi, Visual Basic, Python and t programming language.

Kvaser CAN hardware is built around the same common software API. Applications developed using one device type will run without modification on other device types.

## Technical Data

<b>Bit Rate</b>	5-1000 kbps
<b>Certificates</b>	CE, RoHS
<b>Channels</b>	1
<b>Connector</b>	DSUB 9
<b>Dimensions</b>	30 x 200 x 17 mm for body incl. strain relief
<b>Error Frame Generation</b>	No
<b>Error Counters Reading</b>	No
<b>Galvanic Isolation</b>	Yes
<b>Interfaces</b>	USB, CAN
<b>Messages Per Second Receive</b>	8000 mps
<b>Messages Per Second Sending</b>	8000 mps
<b>Silent Mode</b>	No
<b>Temperature Range</b>	-40 to +70 °C
<b>Weight</b>	148 g