





Learn more about  
this product




## Your Gateway to Efficient Connectivity

The Kvaser U100P-X2 is a robust, single-channel CAN/CAN FD to USB interface with reinforced galvanic isolation that squarely addresses the needs of the evolving automotive development market. Fully compatible with J1939, CANopen, NMEA 2000® and DeviceNet, this is the first in a new range of interfaces that is also suited to rugged applications in marine, industrial, heavy duty vehicle and heavy industries.

 **Warranty**  
2-Year warranty. See our general conditions and policies for details.

 **Support**  
Free support for all products by contacting [support@kvaser.com](mailto:support@kvaser.com)

 **EAN**  
73-30130-01270-7

## Major Features

- Supports CAN FD, up to 8 Mbit/s (with correct physical layer implementation).
- Supports both 11-bit (CAN 2.0A) and 29-bit (CAN 2.0B active) identifiers.
- Lightweight robust housing made of glass fibre reinforced polyamide overmolded with TPE.
- Intuitive LED UI.
- Reinforced Galvanic Isolation, 5000VAC rms applied for 60 seconds.
- 20 000 msg/s, each timestamped with a resolution of 1  $\mu$ s.
- Support for SocketCAN
- IP67 rated housing.
- Compatible with J1939, CANopen, NMEA 2000® and DeviceNet. Higher layer protocol translation handled by the user's application. For software support please see our Technical Associates products and our Software Download page ([www.kvaser.com](http://www.kvaser.com)).

## Support

Documentation, Kvaser CANlib SDK and drivers can be downloaded for free at [www.kvaser.com/downloads](http://www.kvaser.com/downloads).

Kvaser CANlib SDK is a free resource that includes everything you need to develop software for the Kvaser CAN interfaces. Includes full documentation and many program samples, written in C, C++, C#, Delphi, Visual Basic, Python and t programming language.

Kvaser CAN hardware is built around the same common software API. Applications developed using one device type will run without modification on other device types.

## Technical Data

<b>CAN Bit Rate</b>	10 kbit/s to 1 Mbit/s
<b>CAN Channels</b>	1
<b>CAN Transceivers</b>	11898-2 Compliant
<b>Certifications</b>	CE, RoHS
<b>Connector</b>	M12 5 pin
<b>Current Consumption</b>	Typical 250 mA
<b>Dimensions</b>	38 x 128 x 26 mm
<b>Error Frame Detection</b>	Yes
<b>Error Frame Generation</b>	Yes
<b>Galvanic Isolation</b>	Yes
<b>MagiSync</b>	Yes
<b>Operating Systems</b>	Windows, Linux
<b>Silent Mode</b>	Yes
<b>Temperature Range</b>	-40 to +85 °C
<b>Timestamp Resolution</b>	1 $\mu$ s
<b>Weight</b>	160 g